## **TS-1215 OVERVIEW**



## **Delivering Clean, Quiet Power**

The TS-1215 Linear Power Supply was designed from the ground up to deliver ultra-clean, noise-free dc power to antennas and RF amplifiers.

With a footprint about the size of an index card, this small unit packs all the essential features demanded by today's RF professionals:

- Small footprint
- 110/220 V ac operation
- 50/60 Hz
- On/Off switch with LED indicator
- Separate 12 and 15 V dc outputs for different devices
- Internal linear encapsulated power modules
- Wide operating temperature

Optional versions are available to meet any requirement, including 5, 10, 24, 48, 50, 75 and 100 V dc versions. For those who need only one dc output, we can configure the unit for twice the output amperage.

The key to this unit is a specialized EMI filter to ensure only clean dc is delivered to the destination device. Coupled with its compact design, it's an ideal option when searching for a perfect linear supply. Also included is a ruggedized mounting plate for OEM applications.

The cleanest and most reliable linear power supply on the market, designed to deliver ultra-quiet dc power to noise-sensitive equipment

## **Specifications**

/	
Output	12 V dc; 15 V dc
Current	500 mA
Regulation	Line: 0.02%; Load: 0.10%
Ripple mV RMS	0.5
Sloe Blow (A)	1/5
Isolation resistance	50 Ω (TBD)
Protection	Short-circuit protection
Operating temperature range	−25 to +71 °C −13 to +160 °F
Cooling	Air-free cooling
Size $(h \times w \times d)$	$3.5 \times 5.3 \times 3.75$ in



## **CONTACT US TODAY**

To schedule a demonstration, or for more information, including pricing and availability on this or any of our products, call, e-mail or visit us online.



© 2017 Transformational Security, LLC. Specifications subject to change.